

20 kw – 400 kw Generator Sets

Thompson
Power Systems



- Multivoltage, 1 ϕ and 3 ϕ
- Isochronous Governors
- Convenience Outlets
- Remote Auto Start/Stop Capability
- Emission Certified
- 110% Secondary Containment
- Sound Attenuated

SPECIFICATIONS

Model	Generator Set Fuel Consumption GPH	Tank Capacity (Gallons)	Electrical @ 0.8 PF	Weight With Trailer & Fuel	Dimensions (with trailer) *
20 kw	100% load = 1.7 75% load = 1.3 50% load = 1.0	45	69 amps at 208 v 30 amps at 480 v	3,084 lbs	5.3'W x 6'H x 11.3' L
30 kw	100% load = 2.4 75% load = 1.8 50% load = 1.3	58	104 amps at 208 v 45 amps at 480 v	6,480 lbs	6.3'W x 7.3'H x 15.4' L
60 kw	100% load = 5.2 75% load = 4.5 50% load = 3.5	157	208 amps at 208 v 91 amps at 480 v	5,677 lbs	6.3'W x 7.1'H x 15.2' L
100 kw	100% load = 7 75% load = 5.2 50% load = 3.5	182	347 amps at 208 v 150 amps at 480 v	8,470 lbs	6.9'W x 7.8'H x 16'L
150 kw	100% load = 11.2 75% load = 8.5 50% load = 5.9	210	520 amps at 208 v 225 amps at 480 v	12,000 lbs	7'W x 8.4'H x 17.4'L
230 kw	100% load = 18.3 75% load = 13.4 50% load = 9.1	400	781 amps at 208 v 330 amps at 480 v	16,550 lbs	8.4'W x 9.5'H x 20.5'L
300 kw	100% load = 23.5 75% load = 16.8 50% load = 11.8	400	1,040 amps at 208 v 451 amps at 480 v	16,550 lbs	8.4'W x 9.5'H x 20.5'L
400 kw	100% load = 28.0 75% load = 21.0 50% load = 14.0	520	1,390 amps at 208 v 602 amps at 480 v	20,458 lbs	8.5'W x 10.8'H x 22.2'L

* Verify dimensions with Thompson Power for dimensionally critical locations.

www.ThompsonPowerSystems.com/rental

Thompson Power Systems is your source for rental:

- Generators
- Chillers
- Air Conditioners
- Dehumidifiers
- Transformers
- Electrical Distribution



(256) 532-5399 - Huntsville

(205) 244-7800 - Birmingham

(334) 215-5399 - Montgomery

(251) 621-6099 - Mobile

(850) 873-6599 - Panama City